



# Programmer Key

The TRACcess® Programmer Key saves you time and money by giving you the flexibility to reprogram your TRACcess locking devices in the field. The TRACcess Programmer Key receives its instructions from your TRACcess System Administrator through a cradle connected to a personal computer with Internet access. Completed programming activities are uploaded to the TRACcess Manager and any new programming instructions are downloaded to the Programmer Key. Use the Programmer Key to:

- Add and delete up to 15 additional TRACcess System Codes to give other companies shared access to designated sites
- Add or delete key holder lock-out lists
- Change TRACcess locking device access code and turn Access Code Required feature on or off
- Change access hours in TRACcess locking device and turn Timed Access feature on or off
- View and save the last 35 access events from up to 5 TRACcess locking devices

Only an authorized TRACcess Administrator can download system code changes to Programmer Keys that will affect locking devices in their TRACcess inventory. TRACcess Programming Keys cannot receive instructions from other TRACcess systems nor communicate with TRACcess locking devices outside their primary system code.



## Items Included

- Programmer Key cradle
- PC to Cradle serial port connection
- Software disk
- Programmer Key Manual
- Neoprene Carrying Case

Feature	Description		
<b>Size</b>	<b>Width</b>	<b>Height</b>	<b>Depth</b>
Body:	3.33 inches	5.62 inches	1.4 inches
Programming Attachment:	2.1 inches	2.88 inches	0.7 inches
<b>Weight</b>	12 ounces		
<b>Display</b>	Enhanced screen technology — easy to see at all angles, in dim light and in bright sunlight		
<b>Battery Life</b>	Rechargeable Lithium-ion battery automatically recharges in SUPRA® cradle for extended operation		
<b>PC System Requirements</b>	Serial port; Internet Explorer 5.01 or greater		



## Environmental Specifications

Test	Description
Temperature Range	-20°C (-4°F) to 55°C (131°F)
Temperature/Humidity	MIL-STD 202F, Method 106D at 95% relative humidity
Electrostatic Discharge	IEC801-2, 6kV contact discharge, 8kV air discharge
Water Resistance	Passed standard rain test of 0.15 inches per hour
Chemical Resistance	No functional or cosmetic damage when exposed to common cleaning materials

## Programming Features

1. Access TRACcess locking devices
2. Read device tracking history
3. Program TRACcess devices:
  - Add and delete system codes
  - Program lockout list
  - Change access times
  - Change device access code
  - Change Programmer Key PIN code
4. Manually update Programmer Key
5. Release TRAC-Box Shackle



**TRACcess® — One Solution. Infinite Possibilities.**

World Headquarters: 4001 Fairview Industrial Dr. SE • Salem, Oregon USA 97302  
(800) 547-0252 • FAX (800) 375-9852 • [www.supra-products.com](http://www.supra-products.com)

In Canada: 2100 Thurston Dr. Unit 15, Ottawa, Ontario K1G 4K8  
In Canada: (800) 267-6317 • (613) 737-3623 • Fax: (613) 737-5517

